

## SIESTA S6

Bedside DAB/DAB+ and FM alarm clock radio with Bluetooth and CrystalVue+™ display



### Top 5 features

- **4 alarms** – set different alarm times for the weekdays, weekends and more
- Use **Bluetooth** to play your own music collection wirelessly
- **Ultra-clear CrystalVue+™ display** that adjusts to all lighting conditions
- Hit the **Siesta Button** for a quick power nap
- **USB PowerPort** to charge your mobile without taking up a socket

SIESTA S6



### Colour variants

Graphite, Polar



### Watch the video

[www.pure.com/siesta-s6](http://www.pure.com/siesta-s6)



PURE



## Technical specifications

- **Radio:** Digital (DAB/DAB+) and FM
- **Frequencies:** FM radio 87.5 - 108MHz
- **Presets:** 40 (20 DAB and 20 FM)
- **Bluetooth:** Bluetooth v4.1, A2DP support
- **Speaker:** Full-range 2.5" drive unit
- **Audio power output:** 2W RMS amplifier
- **Input connectors:** 5.5V (2A) Micro USB power adapter socket (also for software updates)
- **Output connectors:** USB-A (1A) socket for charging phone or tablet, 3.5mm headphone socket
- **Power supply:** 100-240V AC to 5.5V (2A) DC micro USB external power adapter
- **Aerial:** Wire aerial attached
- **Dimensions:** 146mm (Width) x 140mm (Depth) x 70mm (Height)
- **Weight:** 305 g
- **Warranty:** Comprehensive three year warranty
- **Approvals:** CE Marked. Hereby Pure International Limited declares that the radio equipment type Siesta S6 is compliant with Directive 2014/53/EU and RoHS Directive (2011/65/EU). ETSI EN300 401 compliant. See Pure web-site for full text.



## Comparison chart

	Siesta S2	Siesta Rise	Siesta Rise S	Siesta Rise Marius	Siesta S6
<b>DAB/DAB+/FM wavebands</b>	✓	✓	✓	✓	✓
<b>Display</b>	CrystalVue	CrystalVue	CrystalVue	CrystalVue	CrystalVue+
<b>Bluetooth</b>			✓	✓	✓
<b>Alarms</b>	2	3	3	3	4
<b>Sleep timer</b>	✓	✓	✓	✓	✓
<b>Kitchen timer</b>	✓	✓	✓	✓	✓
<b>USB charging</b>		✓	✓	✓	✓
<b>Tone controls</b>		✓	✓	✓	✓
<b>Presets</b>	10	20	20	20	40
<b>Backlit buttons</b>			✓	✓	✓
<b>SnoozeTouch</b>					✓
<b>Siesta button</b>					✓



### Contact us

Andy Graham | [andy.graham@pure.com](mailto:andy.graham@pure.com) | [www.pure.com](http://www.pure.com)

**PURE**